

表二五九～二 三相電動機堵轉電流轉換

電壓 (V) 最大堵轉 電流(A) 馬力(hp)	115	200	208	220	380	440
$\frac{1}{2}$	40	23	22.1	20.9	12	10.5
$\frac{3}{4}$	50	28.8	27.6	26.1	15	13.1
1	60	34.5	33	31	18	15.5
$1\frac{1}{2}$	80	46	44	42	24	21.0
2	100	57.5	55	52	30	26.0
3	—	73.6	71	67	39	33.5
5	—	105.8	102	96	56	48.0
$7\frac{1}{2}$	—	146	140	132	77	66.0
10	—	186.3	179	169	98	84.5
15	—	267	257	243	141	121.5
20	—	334	321	303	176	151.5
25	—	420	404	382	221	191.0
30	—	500	481	455	263	227.5
40	—	667	641	606	351	303.0
50	—	834	802	758	439	379.0
60	—	1,001	962	910	527	455.0
75	—	1,248	1,200	1,135	657	567.5
100	—	1,668	1,603	1,516	878	758.0
125	—	2,087	2,007	1,898	1,098	949.0
150	—	2,496	2,400	2,269	1,314	1134.5
200	—	3,335	3,207	3,032	1,755	1516.0